



## Impulse switch ESR12Z-4DX-UC



**Eltako**

ESR12Z-4DX-UC

21400301

4010312108130 EAN/GTIN

**50,51 GBP** excl. VAT\*\*  
plus shipping



3-5 days\* (GBR)

Impulse switch ESR12Z-4DX-UC electronic function for central control, mounting type DIN rail, width in modular units 1, installation depth 58mm, number of contacts as NO contact 1, number of contacts as NC contact 0, number of contacts as changeover contact 0, control voltage 1 8 ... 253V, type of control voltage 1 AC, frequency of control voltage 1 50 ... 50Hz, control voltage 2 10 ... 230V, type of control voltage 2 DC, frequency of control voltage 2 50 ... 50Hz, rated switching current 16A, supply voltage 230 ... 230V, type of voltage of supply voltage AC/DC, max. incandescent lamp load 2000W, max. fluorescent lamp load 1000VA, max. fluorescent lamp load (duo circuit) 1000VA, max. fluorescent lamp load (parallel compensated) 500VA, max. switching current (cos phi = 0.6) 8A, manual operation possible, 4-way impulse switching relay, also for central and group control. With 4 independent contacts. Standby loss only 0.03 to 0.4 watts. Simply connect the N conductor to the terminal (N) and the outer conductor to 1(L), 3(L) or 5(L). This results in an additional stand-by consumption of only 0.1 watts. If the contact is used to control switching devices that do not switch at zero crossing themselves, (N) should not be connected, otherwise the additional closing delay will have the opposite effect. Local universal control voltage 8..230V UC. With additional universal voltage control inputs centrally on and off for 8..230V UC, electrically isolated from the local control inputs. With additional group control inputs on and off for 8..230V UC. Same potential as the local control inputs. Groups of these impulse switches can be controlled separately in a central control system via the group control inputs. Supply voltage same as local control voltage. The latest hybrid technology combines the advantages of wear-free electronic control with the high performance of special relays. Due to the use of bistable relays, there is no coil power loss and no heating as a result, even when switched on. After installation, wait for the brief automatic synchronization before connected consumers are connected to the mains. Central commands always have priority, the local control inputs are blocked during the central command. If the supply voltage fails, the system is switched off in a defined manner.

## YOUR ADVANTAGES



### WORLDWIDE TRADE

Corporate video eibmarkt®



### COMPLAINTS HANDLING

Obliging and 100% safely



### SHORT DELIVERY TIME

Warehousing



### 99% CUSTOMER SATISFACTION

> 500,000 customers worldwide



### 25 YEARS OF EXPERIENCE

In worldwide mail order



### REFUND

Within 14 days



### DHL TRACK & TRACE

Shipment tracking



### ORDER LIVE CHAT

With order history



### DATA PROTECTION

Guarantee

© 1997-2024 eibmarkt.com GmbH - Kemmlerstrasse 1 - 08527 Plauen - Germany

eibabo® and eibmarkt® are registered trademarks of EIBMARKT® GmbH holding company ([www.eibmarkt.de](http://www.eibmarkt.de)). eibabo® is a company of eibmarkt.com GmbH. eibmarkt.com GmbH is a 100% subsidiary of EIBMARKT® GmbH holding.

\* Note on delivery time: Day = Monday to Friday, no public holiday in Bavaria or Saxony. Goods are also delivered on Saturdays (DHL).

\*\* Payment methods may vary from country to country. All prices plus shipping and excluding customs duties or other additional costs (import sales tax) for deliveries outside the EU.

\*\*\* Savings compared to RRP = the manufacturer's recommended retail price. RRP is the price recommended to retailers by the manufacturer, importer or wholesaler as a resale price to the customer. The RRP is also referred to as the list price and is defined as the highest possible price that a buyer would pay for a specific product before any discounts (Source of gross list prices: Germany).

eibabo® the Smart Home technology shop  
eibabo® electronics cheap online order  
eibabo® electric appliances buy online

